



# Application Note

## AN\_184

# FTDI Device Input Output Pin States

**Version 3.1**

**Issue Date: 2018-04-19**

This application note describes the reset, suspend and active states of the input / output pins of the following devices: FT232R, FT245R, FT232H, FT2232H, FT4232H, FT2232D, FT200XD, FT201X, FT220X, FT221X, FT230X, FT234XD, FT231X, FT240X, FT120, FT121, FT122, FT313H & FT4222H

Use of FTDI devices in life support and/or safety applications is entirely at the user's risk, and the user agrees to defend, indemnify and hold harmless FTDI from any and all damages, claims, suits or expense resulting from such use.

**Future Technology Devices International Limited (FTDI)**

Unit 1, 2 Seaward Place, Glasgow G41 1HH, United Kingdom

Tel.: +44 (0) 141 429 2777 Fax: + 44 (0) 141 429 2758

Web Site: <http://ftdichip.com>

Copyright © Future Technology Devices International Limited

## **Table of Contents**

<b>1</b>	<b>Introduction .....</b>	<b>3</b>
1.1	<b>Applicable Documents .....</b>	<b>3</b>
<b>2</b>	<b>FT232R – I/O Pins .....</b>	<b>4</b>
2.1	<b>FT232R - CBUS Selected Function.....</b>	<b>5</b>
<b>3</b>	<b>FT245R - I/O Pins .....</b>	<b>6</b>
<b>4</b>	<b>FT232H– I/O Pins.....</b>	<b>7</b>
4.1	<b>FT232H - Selected Function.....</b>	<b>8</b>
<b>5</b>	<b>FT2232H .....</b>	<b>9</b>
5.1	<b>FT2232H – Channel A Pins.....</b>	<b>9</b>
5.2	<b>FT2232H – Channel B Pins.....</b>	<b>10</b>
5.3	<b>FT2232H - Selected Functions .....</b>	<b>11</b>
<b>6</b>	<b>FT4232H .....</b>	<b>12</b>
6.1	<b>FT4232H – Channel A Pins.....</b>	<b>12</b>
6.2	<b>FT4232H – Channel B Pins.....</b>	<b>12</b>
6.3	<b>FT4232H – Channel C Pins.....</b>	<b>13</b>
6.4	<b>FT4232H – Channel D Pins .....</b>	<b>13</b>
6.5	<b>FT4232H - Selected Functions .....</b>	<b>14</b>
<b>7</b>	<b>FT2232D – Channel A Pins.....</b>	<b>15</b>
7.1	<b>FT2232D – Channel B Pins.....</b>	<b>16</b>
7.2	<b>FT2232D - Selected Functions – Channel A.....</b>	<b>17</b>
7.3	<b>FT2232D - Selected Function – Channel B .....</b>	<b>18</b>
<b>8</b>	<b>FT200XD – I/O Pins.....</b>	<b>19</b>
<b>9</b>	<b>FT201X – I/O Pins .....</b>	<b>20</b>
<b>10</b>	<b>FT220X – I/O Pins.....</b>	<b>21</b>
<b>11</b>	<b>FT221X – I/O Pins.....</b>	<b>22</b>
<b>12</b>	<b>FT230X – I/O Pins.....</b>	<b>23</b>

<b>13</b>	<b>FT231X – I/O Pins</b> .....	<b>24</b>
<b>14</b>	<b>FT234XD – I/O Pins</b> .....	<b>25</b>
<b>15</b>	<b>FT240X – I/O Pins</b> .....	<b>26</b>
<b>16</b>	<b>FT120 – I/O Pins</b> .....	<b>27</b>
<b>17</b>	<b>FT121 – I/O Pins</b> .....	<b>28</b>
<b>18</b>	<b>FT122 – I/O Pins</b> .....	<b>29</b>
<b>19</b>	<b>FT313H – I/O Pins</b> .....	<b>30</b>
<b>20</b>	<b>FT4222H Rev A – I/O Pins</b> .....	<b>31</b>
20.1	<b>Configuration Mode 0</b> .....	<b>31</b>
20.2	<b>Configuration Mode 1</b> .....	<b>32</b>
20.3	<b>Configuration Mode 2</b> .....	<b>33</b>
20.4	<b>Configuration Mode 3</b> .....	<b>34</b>
<b>21</b>	<b>FT4222H Rev B,C,D – I/O Pins</b> .....	<b>35</b>
21.1	<b>Configuration Mode 0</b> .....	<b>35</b>
21.2	<b>Configuration Mode 1</b> .....	<b>36</b>
21.3	<b>Configuration Mode 2</b> .....	<b>37</b>
21.4	<b>Configuration Mode 3</b> .....	<b>38</b>
<b>22</b>	<b>Contact Information</b> .....	<b>39</b>
<b>Appendix A – References</b> .....		<b>40</b>
Document References .....		<b>40</b>
Acronyms and Abbreviations.....		<b>40</b>
<b>Appendix B – List of Tables &amp; Figures</b> .....		<b>41</b>
List of Tables.....		<b>41</b>
List of Figures .....		<b>42</b>
<b>Appendix C – Revision History</b> .....		<b>43</b>

## 1 Introduction

This application note explains the various states of input and output pins of the following FTDI devices: FT232R, FT245R, FT232H, FT2232H, FT4232H, FT2232D, FT200XD, FT201X, FT220X, FT221X, FT230X, FT231X, FT234XD, FT240X, FT120, FT121, FT122, FT313H & FT4222H.

**Note:** The convention used throughout this document for active low signals is the signal name followed by a #.

### 1.1 Applicable Documents

The following data sheets can be downloaded by clicking on the appropriate links below:

[FT232R USB UART IC Data Sheet](#)

[FT245R USB FIFO Data Sheet](#)

[FT232H Single Channel Hi-Speed USB to Multipurpose UART/FIFO IC Data Sheet](#)

[FT2232H Hi-Speed Dual USB UART/FIFO IC Data Sheet](#)

[FT4232H Hi-Speed Quad USB UART IC Data Sheet](#)

[FT2232D Dual USB UART/FIFO IC Data Sheet](#)

[FT200XD Full-Speed USB to I2C bridge in 10 pin DFN package Data Sheet](#)

[FT201X Full-Speed USB to I2C bridge Data Sheet](#)

[FT220X Full-Speed USB to 4-bit SPI/FT1248 bridge Data Sheet](#)

[FT221X Full-Speed USB to 8-bit SPI/FT1248 bridge Data Sheet](#)

[FT230X Full-Speed USB to basic UART Data Sheet](#)

[FT231X Full-Speed USB to full handshake UART Data Sheet](#)

[FT234XD Full-Speed USB to basic UART Data Sheet](#)

[FT240X Full-Speed USB to 8-bit FIFO Data Sheet](#)

[FT120 USB Full-Speed Device Controller Data Sheet](#)

[FT121 USB Full-Speed Device Controller Data Sheet](#)

[FT122 USB Full-Speed Device Controller Data Sheet](#)

[FT313H Hi-Speed Host Controller](#)

[FT4222H Hi-Speed Quad SPI/I2C IC Data Sheet](#)

## 2 FT232R – I/O Pins

FT232R							
Pin Name	Pin Number (QFN)	Pin Number (SSOP)	RESET# Low	SUSPEND (Pull Down IO Pins in USB Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
CBUS 0	22	23	TriSt- PU	Selected Function	TriSt-PD	Driving Low	Selected Function
CBUS 1	21	22	TriSt- PU	Selected Function	TriSt-PD	Driving Low	Selected Function
CBUS 2	10	13	TriSt- PU	Selected Function	TriSt-PD	Driving Low	Selected Function
CBUS 3	11	14	TriSt	Selected Function	TriSt-PD	Input	Selected Function
CBUS 4	9	12	TriSt	Selected Function	TriSt-PD	Input	Selected Function
TXD	30	1	TriSt- PU	Output	TriSt-PD	TriSt- PU	Output
DTR#	31	2	TriSt- PU	Output	TriSt-PD	TriSt- PU	Output
RTS#	32	3	TriSt- PU	Output	TriSt-PD	TriSt- PU	Output
RXD	2	5	TriSt- PU	Input - PU	TriSt-PD	TriSt- PU	Input- PU
RI#	3	6	TriSt- PU	Input - PU	TriSt-PD	TriSt- PU	Input - PU
DSR#	6	9	TriSt- PU	Input - PU	TriSt-PD	TriSt- PU	Input - PU
DCD#	7	10	TriSt- PU	Input - PU	TriSt-PD	TriSt- PU	Input - PU
CTS#	8	11	TriSt- PU	Input - PU	TriSt-PD	TriSt- PU	Input - PU

**Table 2.1 FT232R I/O States**

## 2.1 FT232R - CBUS Selected Function

FT232R													
Pin	TXD N	PWRO N#	RXLE D#	TXLE D#	TX & RXLE D#	SLEEP#	CLK 48	CLK 24	CLK 12	CLK 6	I/O Mode	BitBanging WRn	BitBanging RDn
CBUS 0	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
CBUS 1	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
CBUS 2	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	x	✓
CBUS 3	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	x	✓
CBUS 4	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	x	x	x

**Table 2.2 FT232R CBUS Selected Functions**

### 3 FT245R - I/O Pins

FT245R							
Pin Name	Pin Number (QFN)	Pin Number (SSOP)	RESET# Low	SUSPENDED (Pull Down IO Pins in USB Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
RXF#	22	23	TriSt- PU	RXF#	TriSt-PD	Driving Low	Output
TXE#	21	22	TriSt- PU	TXE#	TriSt-PD	Driving Low	Output
RD#	10	13	TriSt- PU	RD#	TriSt-PD	Driving Low	Input
WR	11	14	TriSt	WR#	TriSt-PD	Input	Input
PWREN#	9	12	TriSt	PWREN#	TriSt-PD	Input	PWREN#
D0	30	1	TriSt- PU	TriSt- PU driving when RD# is low	TriSt-PD	TriSt- PU	Input- PU driving when RD# is low
D1	2	5	TriSt- PU	TriSt- PU driving when RD# is low	TriSt-PD	TriSt- PU	Input - PU driving when RD# is low
D2	32	3	TriSt- PU	TriSt- PU driving when RD# is low	TriSt-PD	TriSt- PU	Input - PU driving when RD# is low
D3	8	11	TriSt- PU	TriSt- PU driving when RD# is low	TriSt-PD	TriSt- PU	Input - PU driving when RD# is low
D4	31	2	TriSt- PU	TriSt- PU driving when RD# is low	TriSt-PD	TriSt- PU	Input - PU driving when RD# is low
D5	6	9	TriSt- PU	TriSt- PU driving when RD# is low	TriSt-PD	TriSt- PU	Input - PU driving when RD# is low
D6	7	10	TriSt- PU	TriSt- PU driving when RD# is low	TriSt-PD	TriSt- PU	Input - PU driving when RD# is low
D7	3	6	TriSt- PU	TriSt- PU driving when RD# is low	TriSt-PD	TriSt- PU	Input - PU driving when RD# is low

**Table 3.1 FT245R I/O States**

## 4 FT232H– I/O Pins

FT232H							
Pin Name	Pin Number	RESET# Low	Default	SUSPEND (Pull Down IO Pins in USB Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
ADBUS0	13	TriSt	TXD	Function	TriSt-PD	Output	Function
ADBUS1	14	TriSt -PU	RXD	Function	TriSt-PD	Input-PU	Function
ADBUS2	15	TriSt	RTS#	Function	TriSt-PD	Output	Function
ADBUS3	16	TriSt -PU	CTS#	Function	TriSt-PD	Input-PU	Function
ADBUS4	17	TriSt	DTR#	Function	TriSt-PD	Output	Function
ADBUS5	18	TriSt -PU	DSR#	Function	TriSt-PD	Input-PU	Function
ADBUS6	19	TriSt -PU	DCD#	Function	TriSt-PD	Input-PU	Function
ADBUS7	20	TriSt -PU	RI#	Function	TriSt-PD	Input-PU	Function
ACBUS0	21	TriSt-PU	TriSt-PU	Function/Selecti on	TriSt-PD	TriSt-PU	Function/Select ion
ACBUS1	25	TriSt-PU	TriSt-PU	Function/Selecti on	TriSt-PD	TriSt- PU	Function/Select ion
ACBUS2	26	TriSt-PU	TriSt-PU	Function/Selecti on	TriSt-PD	TriSt- PU	Function/Select ion
ACBUS3	27	TriSt-PU	TriSt-PU	Function/Selecti on	TriSt-PD	TriSt- PU	Function/Select ion
ACBUS4	28	TriSt-PU	TriSt-PU	Function/Selecti on	TriSt-PD	TriSt- PU	Function/Select ion
ACBUS5	29	TriSt-PU	TriSt-PU	Function/Selecti on	TriSt-PD	TriSt- PU	Function/Select ion
ACBUS6	30	TriSt-PU	TriSt-PU	Function/Selecti on	TriSt-PD	TriSt- PU	Function/Select ion
ACBUS7	31	TriSt-PD	TriSt-PU	Input-PD or MPSSE	TriSt-PD	TriSt-PD	Input-PD or MPSSE
ACBUS8	32	TriSt-PU	TriSt-PU	Function/Selecti on	TriSt-PD	TriSt- PU	Function/Select ion
ACBUS9	33	TriSt-PU	TriSt-PU	Function/Selecti on	TriSt-PD	TriSt- PU	Function/Select ion

**Table 4.1 FT232H I/O States**



## 4.1 FT232H - Selected Function

FT232H										
Pin		Pin functions (depends on configuration)								
Pin #	Pin Name	ASYNCRS232	245FIFOSYNC	245FIFO	ASYNCRS232	SYNCRS232	MPSSE	Fast Serial interface	CPU Style FIFO	FT1248
13	ADBU S0	TXD	D0	D0	D0	D0	TCK/SK	FSDI	D0	MIOSI0
14	ADBU S1	RXD	D1	D1	D1	D1	TDI/DO	FSCLK	D1	MIOSI1
15	ADBU S2	RTS#	D2	D2	D2	D2	TDO/DI	FSDO	D2	MIOSI2
16	ADBU S3	CTS#	D3	D3	D3	D3	TMS/CS	FSCTS	D3	MIOSI3
17	ADBU S4	DTR#	D4	D4	D4	D4	GPIOL0	** TriSt-UP	D4	MIOSI4
18	ADBU S5	DSR#	D5	D5	D5	D5	GPIOL1	** TriSt-UP	D5	MIOSI5
19	ADBU S6	DCD#	D6	D6	D6	D6	GPIOL2	** TriSt-UP	D6	MIOSI6
20	ADBU S7	RI#	D7	D7	D7	D7	GPIOL3	** TriSt-UP	D7	MIOSI7
21	ACBU S0	* TXDEN	RXF#	RXF#	ACBUS0	ACBUS0	GPIOH0	** ACBUS0	CS#	SCLK
25	ACBU S1	** ACBUS1	TXE#	TXE#	WRSTB#	WRSTB#	GPIOH1	** ACBUS1	A0	SS_N
26	ACBU S2	** ACBUS2	RD#	RD#	RDSTB#	RDSTB#	GPIOH2	** ACBUS2	RD#	MISO
27	ACBU S3	* RXLED#	WR	WR	ACBUS3	ACBUS3	GPIOH3	** ACBUS3	WR	ACBUS3
28	ACBU S4	* TXLED#	SIWU#	SIWU#	SIWU#	SIWU#	GPIOH4	SIWU#	SIWU#	ACBUS4
29	ACBU S5	** ACBUS5	CLKOUT	ACBUS5	** ACBUS5	** ACBUS5	GPIOH5	** ACBUS5	** ACBUS5	ACBUS5
30	ACBU S6	** ACBUS6	OE#	ACBUS6	ACBUS6	ACBUS6	GPIOH6	** ACBUS6	** ACBUS6	ACBUS6
31	ACBU S7	PWRSVAV#	USBVCC	USBVCC	USBVCC	USBVCC	GPIOH7	USBVCC	USBVCC	USBVCC
32	ACBU S8	** ACBUS8	** ACBUS8	** ACBUS8	** ACBUS8	** ACBUS8	** ACBUS8	** ACBUS8	** ACBUS8	ACBUS8
33	ACBU S9	** ACBUS9	** ACBUS9	** ACBUS9	** ACBUS9	** ACBUS9	** ACBUS9	** ACBUS9	** ACBUS9	ACBUS9

**Table 4.2 FT232H Selected Functions**

Pins marked \* are EEPROM selectable.

Pins marked \*\* default to tri-stated inputs with an internal 75KΩ (approx.) pull up resistor to VCCIO.

Pin marked \*\*\* default to GPIO line with an internal 75KΩ pull down resistor to GND. This pin can be enabled USBVCC mode instead of GPIO mode using the EEPROM.

## 5 FT2232H

### 5.1 FT2232H – Channel A Pins

FT2232H Channel A							
Pin Name	Pin Number	RESET# Low	Default	SUSPEND (Pull Down IO Pins in Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
16	ADBUS0	TriSt	TXD	Function	TriSt-PD	TXD	Function
17	ADBUS1	TriSt-PU	RXD	Function	TriSt-PD	RXD	Function
18	ADBUS2	TriSt	RTS#	Function	TriSt-PD	RTS#	Function
19	ADBUS3	TriSt-PU	CTS#	Function	TriSt-PD	CTS#	Function
21	ADBUS4	TriSt	DTR#	Function	TriSt-PD	DTR#	Function
22	ADBUS5	TriSt-PU	DSR#	Function	TriSt-PD	DSR#	Function
23	ADBUS6	TriSt-PU	DCD#	Function	TriSt-PD	DCD#	Function
24	ADBUS7	TriSt-PU	RI#	Function	TriSt-PD	RI#	Function
26	ACBUS0	TriSt	TXDEN	Function	TriSt-PD	TXDEN	Function
27	ACBUS1	TriSt-PU	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
28	ACBUS2	TriSt-PU	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
29	ACBUS3	TriSt-PU	RXLED#	Function	TriSt-PD	TriSt-PU	Function
30	ACBUS4	TriSt-PU	TXLED#	Function	TriSt-PD	TriSt-PU	Function
32	ACBUS5	TriSt-PU	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
33	ACBUS6	TriSt-PU	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
34	ACBUS7	TriSt-PU	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function

**Table 5.1 FT2232H I/O States Channel A**

## 5.2 FT2232H – Channel B Pins

FT2232H Channel B							
Pin Name	Pin Number	RESET# Low	Default	SUSPEND (Pull Down IO Pins in Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
38	BDBUS0	TriSt	TXD	Function	TriSt-PD	TXD	Function
39	BDBUS1	TriSt-PU	RXD	Function	TriSt-PD	RXD	Function
40	BDBUS2	TriSt	RTS#	Function	TriSt-PD	RTS#	Function
41	BDBUS3	TriSt-PU	CTS#	Function	TriSt-PD	CTS#	Function
43	BDBUS4	TriSt	DTR#	Function	TriSt-PD	DTR#	Function
44	BDBUS5	TriSt-PU	DSR#	Function	TriSt-PD	DSR#	Function
45	BDBUS6	TriSt-PU	DCD#	Function	TriSt-PD	DCD#	Function
46	BDBUS7	TriSt-PU	RI#	Function	TriSt-PD	RI#	Function
48	BCBUS0	TriSt	TXDEN	Function	TriSt-PD	TXDEN	Function
52	BCBUS1	TriSt-PU	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
53	BCBUS2	TriSt-PU	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
54	BCBUS3	TriSt-PU	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
55	BCBUS4	TriSt-PU	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
57	BCBUS5	TriSt-PU	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
58	BCBUS6	TriSt-PU	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
59	BCBUS7	TriSt-PD	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function

**Table 5.2 FT2232H I/O States Channel B**

### 5.3 FT2232H - Selected Functions

<b>FT2232H</b>										
<b>Pin</b>		<b>Pin functions (depends on configuration)</b>								
Pin #	Pin Name	ASYNC Serial (RS232)	245 FIFO SYNC	245 FIFO	ASYNC Bit-bang	SYNC Bit-bang	MPSSE	Fast Serial interface	CPU Style FIFO	Host Bus Emulation
<b>Channel A</b>										
16	ADBUS0	TXD	D0	D0	D0	D0	TCK/SK	USES CHANNEL B	D0	AD0
17	ADBUS1	RXD	D1	D1	D1	D1	TDI/DO		D1	AD1
18	ADBUS2	RTS#	D2	D2	D2	D2	TDO/DI		D2	AD2
19	ADBUS3	CTS#	D3	D3	D3	D3	TMS/CS		D3	AD3
21	ADBUS4	DTR#	D4	D4	D4	D4	GPIOL0		D4	AD4
22	ADBUS5	DSR#	D5	D5	D5	D5	GPIOL1		D5	AD5
23	ADBUS6	DCD#	D6	D6	D6	D6	GPIOL2		D6	AD6
24	ADBUS7	RI#	D7	D7	D7	D7	GPIOL3	D7	AD7	
26	ACBUS0	TXDEN	RXF#	RXF#	**	**	GPIOH0		CS#	A8
27	ACBUS1	**	TXE#	TXE#	WRSTB #	WRSTB #	GPIOH1		A0	A9
28	ACBUS2	**	RD#	RD#	RDSTB#	RDSTB#	GPIOH2		RD#	A10
29	ACBUS3	RXLED#	WR#	WR#	**	**	GPIOH3		WR#	A11
30	ACBUS4	TXLED#	SIWUA	SIWUA	SIWUA	SIWUA	GPIOH4		SIWUA	A12
32	ACBUS5	**	CLKOUT	**	**	**	GPIOH5		**	A13
33	ACBUS6	**	OE#	**	**	**	GPIOH6		**	A14
34	ACBUS7	**	**	**	**	**	GPIOH7		**	A15
<b>Channel B</b>										
38	BDBUS0	TXD		D0	D0	D0	TCK/SK	FSDI	D0	CS#
39	BDBUS1	RXD		D1	D1	D1	TDI/DO	FSCLK	D1	ALE
40	BDBUS2	RTS#		D2	D2	D2	TDO/DI	FSDO	D2	RD#
41	BDBUS3	CTS#		D3	D3	D3	TMS/CS	FSCTS	D3	WR#
43	BDBUS4	DTR#		D4	D4	D4	GPIOL0		D4	IORDY
44	BDBUS5	DSR#		D5	D5	D5	GPIOL1		D5	CLKOUT
45	BDBUS6	DCD#		D6	D6	D6	GPIOL2		D6	I/O0
46	BDBUS7	RI#		D7	D7	D7	GPIOL3		D7	I/O1
48	BCBUS0	TXDEN		RXF#	**	**	GPIOH0		CS#	**
52	BCBUS1	**		TXE#	WRSTB #	WRSTB #	GPIOH1		A0	**
53	BCBUS2	**		RD#	RDSTB#	RDSTB#	GPIOH2		RD#	**
54	BCBUS3	RXLED#		WR#	**	**	GPIOH3		WR#	**
55	BCBUS4	TXLED#		SIWUB	SIWUB	SIWUB	GPIOH4	SIWUB	SIWUB	**
57	BCBUS5	**		**	**	**	GPIOH5		**	**
58	BCBUS6	**		**	**	**	GPIOH6		**	**
59	BCBUS7	PWRSVAV #	PWRSVAV #	PWRSVAV #	PWRSVAV #	PWRSVAV #	GPIOH7	PWRSVAV #	PWRSVAV #	PWRSVAV #

**Table 5.3 FT2232H Selected Functions**

Pins marked \*\* default to tri-stated inputs with an internal 75KΩ (approx.) pull up resistor to VCCIO.

## 6 FT4232H

### 6.1 FT4232H – Channel A Pins

FT4232H Channel A							
Pin Name	Pin Number	RESET# Low	Default	SUSPEND (Pull Down IO Pins in Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
16	ADBUS0	TriSt-PU	TXD	TXD	TriSt-PD	TXD	TXD
17	ADBUS1	TriSt-PU	RXD	RXD	TriSt-PD	RXD	RXD
18	ADBUS2	TriSt-PU	RTS#	RTS#	TriSt-PD	RTS#	RTS#
19	ADBUS3	TriSt-PU	CTS#	CTS#	TriSt-PD	CTS#	CTS#
21	ADBUS4	TriSt-PU	DTR#	DTR#	TriSt-PD	DTR#	DTR#
22	ADBUS5	TriSt-PU	DSR#	DSR#	TriSt-PD	DSR#	DSR#
23	ADBUS6	TriSt-PU	DCD#	DCD#	TriSt-PD	DCD#	DCD#
24	ADBUS7	TriSt-PU	RI#	Selection	TriSt-PD	RI#	Selection

**Table 6.1 FT4232H I/O States Channel A**

### 6.2 FT4232H – Channel B Pins

FT4232H Channel B							
Pin Name	Pin Number	RESET# Low	Default	SUSPEND (Pull Down IO Pins in Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
26	BDBUS0	TriSt-PU	TXD	TXD	TriSt-PD	TXD	TXD
27	BDBUS1	TriSt-PU	RXD	RXD	TriSt-PD	RXD	RXD
28	BDBUS2	TriSt-PU	RTS#	RTS#	TriSt-PD	RTS#	RTS#
29	BDBUS3	TriSt-PU	CTS#	CTS#	TriSt-PD	CTS#	CTS#
30	BDBUS4	TriSt-PU	DTR#	DTR#	TriSt-PD	DTR#	DTR#
32	BDBUS5	TriSt-PU	DSR#	DSR#	TriSt-PD	DSR#	DSR#
33	BDBUS6	TriSt-PU	DCD#	DCD#	TriSt-PD	DCD#	DCD#
34	BDBUS7	TriSt-PU	RI#	Selection	TriSt-PD	RI#	Selection

**Table 6.2 FT4232H I/O States Channel B**

### 6.3 FT4232H – Channel C Pins

FT4232H Channel C							
Pin Name	Pin Number	RESET# Low	Default	SUSPEND (Pull Down IO Pins in Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
48	CDBUS0	TriSt-PU	TXD	TXD	TriSt-PD	TXD	TXD
52	CDBUS1	TriSt-PU	RXD	RXD	TriSt-PD	RXD	RXD
53	CDBUS2	TriSt-PU	RTS#	RTS#	TriSt-PD	RTS#	RTS#
54	CDBUS3	TriSt-PU	CTS#	CTS#	TriSt-PD	CTS#	CTS#
55	CDBUS4	TriSt-PU	DTR#	DTR#	TriSt-PD	DTR#	DTR#
57	CDBUS5	TriSt-PU	DSR#	DSR#	TriSt-PD	DSR#	DSR#
58	CDBUS6	TriSt-PU	DCD#	DCD#	TriSt-PD	DCD#	DCD#
59	CDBUS7	TriSt-PU	RI#	Selection	TriSt-PD	RI#	Selection

**Table 6.3 FT4232H I/O States Channel C**

### 6.4 FT4232H – Channel D Pins

FT4232H Channel D							
Pin Name	Pin Number	RESET# Low	Default	SUSPEND (Pull Down IO Pins in Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
26	DDBUS0	TriSt-PU	TXD	TXD	TriSt-PD	TXD	TXD
27	DDBUS1	TriSt-PU	RXD	RXD	TriSt-PD	RXD	RXD
28	DDBUS2	TriSt-PU	RTS#	RTS#	TriSt-PD	RTS#	RTS#
29	DDBUS3	TriSt-PU	CTS#	CTS#	TriSt-PD	CTS#	CTS#
30	DDBUS4	TriSt-PU	DTR#	DTR#	TriSt-PD	DTR#	DTR#
32	DDBUS5	TriSt-PU	DSR#	DSR#	TriSt-PD	DSR#	DSR#
33	DDBUS6	TriSt-PU	DCD#	DCD#	TriSt-PD	DCD#	DCD#
34	DDBUS7	TriSt-PD	RI#	Selection	TriSt-PD	RI#	Selection

**Table 6.4 FT4232H I/O States Channel D**

## 6.5 FT4232H - Selected Functions

<b>FT4232H</b>					
<b>Pins</b>		<b>Pin functions (depend on configuration)</b>			
Pin #	Pin Name	ASYNC Serial (RS232)	ASYNC Bit-bang	SYNC Bit-bang	MPSSE
<b>Channel A</b>					
16	ADBUS0	TXD	D0	D0	TCK/SK
17	ADBUS1	RXD	D1	D1	TDI/DO
18	ADBUS2	RTS#	D2	D2	TDO/DI
19	ADBUS3	CTS#	D3	D3	TMS/CS
21	ADBUS4	DTR#	D4	D4	GPIOLO
22	ADBUS5	DSR#	D5	D5	GPIOL1
23	ADBUS6	DCD#	D6	D6	GPIOL2
24	ADBUS7	RI#/ TXDEN*	D7	D7	GPIOL3
<b>Channel B</b>					
26	BDBUS0	TXD	D0	D0	TCK/SK
27	BDBUS1	RXD	D1	D1	TDI/DO
28	BDBUS2	RTS#	D2	D2	TDO/DI
29	BDBUS3	CTS#	D3	D3	TMS/CS
30	BDBUS4	DTR#	D4	D4	GPIOLO
32	BDBUS5	DSR#	D5	D5	GPIOL1
33	BDBUS6	DCD#	D6	D6	GPIOL2
34	BDBUS7	RI#/ TXDEN*	D7	D7	GPIOL3
<b>Channel C</b>					
38	CDBUS0	TXD	D0	D0	RS232 or Bit-Bang interface
39	CDBUS1	RXD	D1	D1	RS232 or Bit-Bang interface
40	CDBUS2	RTS#	D2	D2	RS232 or Bit-Bang interface
41	CDBUS3	CTS#	D3	D3	RS232 or Bit-Bang interface
43	CDBUS4	DTR#	D4	D4	RS232 or Bit-Bang interface
44	CDBUS5	DSR#	D5	D5	RS232 or Bit-Bang interface
45	CDBUS6	DCD#	D6	D6	RS232 or Bit-Bang interface
46	CDBUS7	RI#/ TXDEN*	D7	D7	RS232 or Bit-Bang interface
<b>Channel D</b>					
48	DDBUS0	TXD	D0	D0	RS232 or Bit-Bang interface
52	DDBUS1	RXD	D1	D1	RS232 or Bit-Bang interface
53	DDBUS2	RTS#	D2	D2	RS232 or Bit-Bang interface
54	DDBUS3	CTS#	D3	D3	RS232 or Bit-Bang interface
55	DDBUS4	DTR#	D4	D4	RS232 or Bit-Bang interface
57	DDBUS5	DSR#	D5	D5	RS232 or Bit-Bang interface
58	DDBUS6	DCD#	D6	D6	RS232 or Bit-Bang interface
59	DDBUS7	RI#/ TXDEN*	D7	D7	RS232 or Bit-Bang interface

**Table 6.5 Selected Functions**

## 7 FT2232D – Channel A Pins

FT2232D Channel A							
Pin Name	Pin Number	RESET# Low	Default	SUSPEND (Pull Down IO Pins in Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
24	ADBUS0	TriSt	TXD	Function	TriSt- PD	TriSt	Function
23	ADBUS1	TriSt-PU	RXD	Function	TriSt- PD	TriSt-PU	Function
22	ADBUS2	TriSt	RTS#	Function	TriSt- PD	TriSt	Function
21	ADBUS3	TriSt-PU	CTS#	Function	TriSt- PD	TriSt-PU	Function
20	ADBUS4	TriSt	DTR#	Function	TriSt- PD	TriSt	Function
19	ADBUS5	TriSt-PU	DSR#	Function	TriSt- PD	TriSt-PU	Function
17	ADBUS6	TriSt-PU	DCD#	Function	TriSt- PD	TriSt-PU	Function
16	ADBUS7	TriSt-PU	RI#	Function	TriSt- PD	TriSt-PU	Function
15	ACBUS0	TriSt	TXDEN	Function	TriSt- PD	TriSt	Function
13	ACBUS1	TriSt	SLEEP#	Function	TriSt- PD	TriSt	Function
12	ACBUS2	TriSt-PU	RXLED#	Function	TriSt- PD	TriSt-PU	Function
11	ACBUS3	TriSt-PU	TXLED#	Function	TriSt- PD	TriSt-PU	Function

**Table 7.1 FT2232D I/O States Channel A**



## 7.1 FT2232D – Channel B Pins

FT2232D Channel B							
Pin Name	Pin Number	RESET# Low	Default	SUSPEND (Pull Down IO Pins in Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
40	BDBUS0	TriSt	TXD	Function	TriSt- PD	TriSt	Function
39	BDBUS1	TriSt-PU	RXD	Function	TriSt- PD	TriSt-PU	Function
38	BDBUS2	TriSt	RTS#	Function	TriSt- PD	TriSt	Function
37	BDBUS3	TriSt-PU	CTS#	Function	TriSt- PD	TriSt-PU	Function
36	BDBUS4	TriSt	DTR#	Function	TriSt- PD	TriSt	Function
35	BDBUS5	TriSt-PU	DSR#	Function	TriSt- PD	TriSt-PU	Function
33	BDBUS6	TriSt-PU	DCD#	Function	TriSt- PD	TriSt-PU	Function
32	BDBUS7	TriSt-PU	RI#	Function	TriSt- PD	TriSt-PU	Function
30	BCBUS0	TriSt	TXDEN	Function	TriSt- PD	TriSt	Function
29	BCBUS1	TriSt	SLEEP#	Function	TriSt- PD	TriSt	Function
28	BCBUS2	TriSt-PU	RXLED#	Function	TriSt- PD	TriSt-PU	Function
27	BCBUS3	TriSt-PU	TXLED#	Function	TriSt- PD	TriSt-PU	Function

**Table 7.2 FT2232D I/O States Channel B**

## 7.2 FT2232D - Selected Functions – Channel A

Pin#	Generic Pin name	Pin Definitions by Chip Mode <b>**Note 1</b>						
		232 UART Mode	245 FIFO	Enhanced Asynchronous and Synchronous Serial	MPSSE <b>**Note 3</b>	MCU Host Bus Emulation Mode <b>**Note 4</b>	Fast Opto-Isolated Serial Mode	CPU FIFO Interface Mode
24	ADBUS0	TXD	D0	D0	TCK/SK AD0	<b>**Note 2</b>	D0	D0
23	ADBUS1	RXD	D1	D1	TDI/D0	AD1	D1	D1
22	ADBUS2	RTS#	D2	D2	TDO/DI	AD2	D2	D2
21	ADBUS3	CTS#	D3	D3	TMS/CS AD3	D3		D3
20	ADBUS4	DTR#	D4	D4	GPIOL0	AD4	D4	D4
19	ADBUS5	DSR#	D5	D5	GPIOL1	AD5	D5	D5
17	ADBUS6	DCD#	D6	D6	GPIOL2	AD6	D6	D6
16	ADBUS7	RI#	D7	D7	GPIOL3	AD7	D7	D7
15	ACBUS0	TXDEN	RXF#	WR# <b>**Note 5</b>	GPIOH0	I/O0	CS#	CS#
13	ACBUS1	SLEEP#	TXE#	RD# <b>**Note 5</b>	GPIOH1	I/O1	A0	A0
12	ACBUS2	RXLED#	RD#	WR# <b>**Note 6</b>	GPIOH2	IORDY	RD#	RD#
24	ADBUS0	TXD	D0	D0	TCK/SK AD0	<b>**Note 2</b>	D0	
11	ACBUS3	TXLED#	WR	RD# <b>**Note 6</b>	GPIOH3	OSC	WR#	WR#

**Table 7.3 Pin Definition by Chip Mode - Channel A**

**\*\*Note 1:** 232 UART, 245 FIFO, CPU FIFO Interface, and Fast Opto-Isolated modes are enabled in the external EEPROM. Enhanced Asynchronous and Synchronous Bit-Bang modes, MPSSE, and MCU Host Bus Emulation modes are enabled using the driver command set bit mode.

**\*\*Note 2:** Channel A can be configured in another IO mode if channel B is in Fast Opto-Isolated Serial Mode. If both Channel A and Channel B are in Fast Opto-Isolated Serial Mode all of the IO will be on Channel B.

**\*\*Note 3:** MPSSE is Channel A only.

**\*\*Note 4:** MCU Host Bus Emulation requires both Channels.

**\*\*Note 5:** The Bit-Bang Mode (synchronous and asynchronous) WR# and RD# strobes are on these pins when the main Channel mode is 245 FIFO, CPU FIFO interface, or Fast Opto-Isolated Serial Modes.

**\*\*Note 6:** The Bit-Bang Mode (synchronous and asynchronous) WR# and RD# strobes are on these pins when the main Channel mode is 232 UART Mode.

### 7.3 FT2232D - Selected Function – Channel B

Pin#	Generic Pin name	Pin Definitions by Chip Mode <b>**Note 1</b>						
		232 UART Mode	245 FIFO	Enhanced Asynchronous and Synchronous Serial	MPSSE <b>**Note 3</b>	MCU Host Bus Emulation Mode <b>**Note 4</b>	Fast Opto-Isolated Serial Mode	CPU FIFO Interface Mode
40	BDBUS0	TXD	D0	D0	A8	FSDI	D0	D0
39	BDBUS1	RXD	D1	D1	A9	FSCLK	D1	D1
38	BDBUS2	RTS#	D2	D2	A10	FSDO	D2	D2
37	BDBUS3	CTS#	D3	D3	A11	FSCTS	D3	D3
36	BDBUS4	DTR#	D4	D4	A12	<b>**Note 2</b>	D4	D4
35	BDBUS5	DSR#	D5	D5	A13	D5		D5
33	BDBUS6	DCD#	D6	D6	A14	D6		D6
32	BDBUS7	RI#	D7	D7	A15	D7		D7
30	BCBUS0	TXDEN	RXF#	WR# <b>**Note 7</b>	CS#	CS#		CS#
29	BCBUS1	SLEEP#	TXE#	RD# <b>**Note 7</b>	ALE	A0		A0
28	BCBUS2	RXLED#	RD#	WR# <b>**Note 6</b>	RD#	RD#		RD#
27	BCBUS3	TXLED#	WR	RD# <b>**Note 6</b>	WR#	WR#		WR#

**Table 7.4 Pin Definition by Chip Mode - Channel B**

**\*\*Note 1:** 232 UART, 245 FIFO, CPU FIFO Interface, and Fast Opto-Isolated modes are enabled in the external EEPROM. Enhanced Asynchronous and Synchronous Bit-Bang modes, MPSSE, and MCU Host Bus Emulation modes are enabled using the driver command set bit mode.

**\*\*Note 2:** Channel A can be configured in another IO mode if channel B is in Fast Opto-Isolated Serial Mode. If both Channel A and Channel B are in Fast Opto-Isolated Serial Mode all of the IO will be on Channel B.

**\*\*Note 3:** MPSSE is Channel A only.

**\*\*Note 4:** MCU Host Bus Emulation requires both Channels.

**\*\*Note 5:** The Bit-Bang Mode (synchronous and asynchronous) WR# and RD# strobes are on these pins when the main Channel mode is 245 FIFO, CPU FIFO interface, or Fast Opto-Isolated Serial Modes.

**\*\*Note 6:** The Bit-Bang Mode (synchronous and asynchronous) WR# and RD# strobes are on these pins when the main Channel mode is 232 UART Mode.

**\*\*Note 7:** The Bit-Bang Mode (synchronous and asynchronous) WR# and RD# strobes are on these pins when the main Channel mode is 245 FIFO, CPU FIFO interface. Bit-Bang mode is not available on Channel B when Fast Opto-Isolated Serial Mode is enabled.

## 8 FT200XD – I/O Pins

FT200XD						
Pin Name	Pin Number	RESET# Low	SUSPEND (Pull Down IO Pins in USB Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
SDA	8	TriSt-PU	SDA	TriSt-PD	SDA	SDA
SCL	6	TriSt-PU	SCL	TriSt-PD	SCL	SCL
CBUS0	5	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function

**Table 8.1 FT200XD I/O States**

**Note 1:** When used in Input Mode, the input pins are pulled to VCCIO via internal 75kΩ (approx.) resistors. These pins can be programmed to gently pull low during USB suspend (PWREN# = "1") by setting an option in the MTP memory.

**Note 2:** Clock stretching is not supported.

## 9 FT201X – I/O Pins

FT201X							
Pin Name	Pin Number (QFN)	Pin Number (SSOP)	RESET# Low	SUSPEND (Pull Down IO Pins in USB Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend – Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
SDA	2	4	TriSt-PU	SDA	TriSt-PD	SDA	SDA
SCL	16	2	TriSt-PU	SCL	TriSt-PD	SCL	SCL
CBUS 0	12	15	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
CBUS 1	11	14	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
CBUS 2	5	7	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
CBUS 3	14	16	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
CBUS 4	4	6	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
CBUS 5	15	1	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function

**Table 9.1 FT201X I/O States**

**Note 1:** When used in Input Mode, the input pins are pulled to VCCIO via internal 75kΩ (approx.) resistors. These pins can be programmed to gently pull low during USB suspend (PWREN# = "1") by setting an option in the MTP memory.

**Note 2:** Clock stretching is not supported.

## 10 FT220X – I/O Pins

FT220X							
Pin Name	Pin Number (QFN)	Pin Number (SSOP)	RESET# Low	SUSPEND (Pull Down IO Pins in USB Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
MIOSIO[0]	15	1	TriSt-PU	MIOSIO[0]	TriSt-PD	MIOSIO[0]	MIOSIO[0]
MIOSIO[1]	2	4	TriSt-PU	MIOSIO[1]	TriSt-PD	MIOSIO[1]	MIOSIO[1]
MIOSIO[2]	16	2	TriSt-PU	MIOSIO[2]	TriSt-PD	MIOSIO[2]	MIOSIO[2]
MIOSIO[3]	4	6	TriSt-PU	MIOSIO[3]	TriSt-PD	MIOSIO[3]	MIOSIO[3]
CLK	12	15	TriSt-PU	CLK (Input-PU)	TriSt-PD	CLK (Input-PU)	CLK (Input-PU)
CS#	11	14	TriSt-PU	CS# (Input-PU)	TriSt-PD	CS# (Input-PU)	CS# (Input-PU)
MISO	5	7	TriSt-PU	MISO	TriSt-PD	MISO	MISO
CBUS3	14	16	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function

**Table 10.1 FT220X I/O States**

**Note:** When used in Input Mode, the input pins are pulled to VCCIO via internal 75kΩ (approx.) resistors. These pins can be programmed to gently pull low during USB suspend (PWREN# = "1") by setting an option in the MTP memory.

## 11 FT221X – I/O Pins

FT221X							
Pin Name	Pin Number (QFN)	Pin Number (SSOP)	RESET# Low	SUSPEND (Pull Down IO Pins in USB Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
MIOSIO[0]	17	20	TriSt-PU	MIOSIO[0]	TriSt-PD	MIOSIO[0]	MIOSIO[0]
MIOSIO[1]	1	4	TriSt-PU	MIOSIO[1]	TriSt-PD	MIOSIO[1]	MIOSIO[1]
MIOSIO[2]	19	2	TriSt-PU	MIOSIO[2]	TriSt-PD	MIOSIO[2]	MIOSIO[2]
MIOSIO[3]	6	9	TriSt-PU	MIOSIO[3]	TriSt-PD	MIOSIO[3]	MIOSIO[3]
MIOSIO[4]	18	1	TriSt-PU	MIOSIO[4]	TriSt-PD	MIOSIO[4]	MIOSIO[4]
MIOSIO[5]	4	7	TriSt-PU	MIOSIO[5]	TriSt-PD	MIOSIO[5]	MIOSIO[5]
MIOSIO[6]	5	8	TriSt-PU	MIOSIO[6]	TriSt-PD	MIOSIO[6]	MIOSIO[6]
MIOSIO[7]	2	5	TriSt-PU	MIOSIO[7]	TriSt-PD	MIOSIO[7]	MIOSIO[7]
CLK	15	18	TriSt-PU	Input-PU	TriSt-PD	Input-PU	CLK(Input-PU)
CS#	14	17	TriSt-PU	Input-PU	TriSt-PD	Input-PU	CS#(Input-PU)
MISO	7	10	TriSt-PU	MISO	TriSt-PD	MISO	MISO
CBUS3	16	19	TriSt-PU	Function	TriSt-PD	Function	Function

**Table 11.1 FT221X I/O States**

**Note:** When used in Input Mode, the input pins are pulled to VCCIO via internal 75kΩ (approx.) resistors. These pins can be programmed to gently pull low during USB suspend (PWREN# = "1") by setting an option in the MTP memory.

## 12 FT230X – I/O Pins

FT230X							
Pin Name	Pin Number (QFN)	Pin Number (SSOP)	RESET# Low	SUSPEND (Pull Down IO Pins in USB Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
TXD	15	1	TriSt-PU	TXD	TriSt-PD	TXD	Output (TXD)
RXD	2	4	TriSt-PU	RXD	TriSt-PD	RXD	Input (RXD)
RTS#	16	2	TriSt-PU	RTS#	TriSt-PD	RTS#	Output (RTS#)
CTS#	4	6	TriSt-PU	CTS#	TriSt-PD	CTS#	Input (CTS#)
CBUS0	12	15	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
CBUS1	11	14	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
CBUS2	5	7	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
CBUS3	14	16	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function

**Table 12.1 FT230X I/O States**

**Note:** When used in Input Mode, the input pins are pulled to VCCIO via internal 75kΩ (approx.) resistors. These pins can be programmed to gently pull low during USB suspend (PWREN# = "1") by setting an option in the MTP memory.



## 13 FT231X – I/O Pins

FT231X							
Pin Name	Pin Number (QFN)	Pin Number (SSOP)	RESET# Low	SUSPEND (Pull Down IO Pins in USB Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
TXD	17	20	TriSt-PU	TXD	TriSt-PD	TXD	TXD
RXD	1	4	TriSt-PU	RXD	TriSt-PD	RXD	RXD
RTS#	19	2	TriSt-PU	RTS#	TriSt-PD	RTS#	RTS#
CTS#	6	9	TriSt-PU	CTS#	TriSt-PD	CTS#	CTS#
DTR#	18	1	TriSt-PU	DTR#	TriSt-PD	DTR#	DTR#
DSR#	4	7	TriSt-PU	DSR#	TriSt-PD	DSR#	DSR#
DCD#	5	8	TriSt-PU	DCD#	TriSt-PD	DCD#	DCD#
RI#	2	5	TriSt-PU	RI#	TriSt-PD	RI#	RI#
CBUS0	15	18	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
CBUS1	14	17	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
CBUS2	7	10	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
CBUS3	16	19	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function

**Table 13.1 FT231X I/O States**

**Note:** When used in Input Mode, the input pins are pulled to VCCIO via internal 75kΩ (approx.) resistors. These pins can be programmed to gently pull low during USB suspend (PWREN# = "1") by setting an option in the MTP memory.

## 14 FT234XD – I/O Pins

FT234XD						
Pin Name	Pin Number	RESET# Low	SUSPEND (Pull Down IO Pins in USB Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
TXD	7	TriSt-PU	TXD	TriSt-PD	TXD	Output (TXD)
RXD	10	TriSt-PU	RXD	TriSt-PD	RXD	Input (RXD)
RTS#	8	TriSt-PU	RTS#	TriSt-PD	RTS#	Output (RTS#)
CTS#	11	TriSt-PU	CTS#	TriSt-PD	CTS#	Input (CTS#)
CBUS0	6	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function

**Table 14.1 FT234XD I/O States**

**Note:** When used in Input Mode, the input pins are pulled to VCCIO via internal 75kΩ (approx.) resistors. These pins can be programmed to gently pull low during USB suspend (PWREN# = "1") by setting an option in the MTP memory.

## 15 FT240X – I/O Pins

FT240X							
Pin Name	Pin Number (QFN)	Pin Number (SSOP)	RESET# Low	SUSPEND (Pull Down IO Pins in USB Suspend - Not Set)	SUSPEND (Pull Down IO Pins in USB Suspend - Set)	During Enumeration (out of reset prior to EEPROM read)	Active (device enumerated after eeprom read)
RESET#	13	16	Input-PU	Input-PU	Input-PU	Input-PU	Input-PU
SIWU#	7	10	TriSt-PU	Input-PU	TriSt-PD	Input-PU	Input-PU
CBUS5	20	23	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
CBUS6	19	22	TriSt-PU	Function	TriSt-PD	TriSt-PU	Function
D0	21	24	TriSt-PU	D0	TriSt-PD	D0	D0
D1	1	4	TriSt-PU	D1	TriSt-PD	D1	D1
D2	23	2	TriSt-PU	D2	TriSt-PD	D2	D2
D3	6	9	TriSt-PU	D3	TriSt-PD	D3	D3
D4	22	1	TriSt-PU	D4	TriSt-PD	D4	D4
D5	4	7	TriSt-PU	D5	TriSt-PD	D5	D5
D6	5	8	TriSt-PU	D6	TriSt-PD	D6	D6
D7	2	5	TriSt-PU	D7	TriSt-PD	D7	D7
RD#	8	11	TriSt-PU	RD# (Input-PU)	TriSt-PD	RD# (Input-PU)	RD# (Input-PU)
WR	9	12	TriSt-PU	WR (Input-PD)	TriSt-PD	WR (Input-PD)	WR (Input-PD)
TXE#	17	20	TriSt-PU	TXE# (OP)	TriSt-PD	TXE# (OP)	TXE# (OP)
RXF#	18	21	TriSt-PU	RXF# (OP)	TriSt-PD	RXF# (OP)	RXF# (OP)

**Table 15.1 FT240X I/O States**

**Note:** When used in Input Mode, the input pins are pulled to VCCIO via internal 75kΩ (approx.) resistors. These pins can be programmed to gently pull low during USB suspend (PWREN# = "1") by setting an option in the MTP memory.

## 16 FT120 – I/O Pins

FT120						
Pin Name	Pin Number (QFN)	Pin Number (TSSOP)	RESET# Low	SUSPEND	During Enumeration (out of reset)	Active (device enumerated)
DATA0	26	1	TriSt	TriSt	TriSt, driving when RD_N is low and CS_N or DMACK_N is low	TriSt, driving when RD_N is low and CS_N is low or DMACK_N is low
DATA1	27	2	TriSt	TriSt		
DATA2	28	3	TriSt	TriSt		
DATA3	1	4	TriSt	TriSt		
DATA4	2	6	TriSt	TriSt		
DATA5	3	7	TriSt	TriSt		
DATA6	4	8	TriSt	TriSt		
DATA7	5	9	TriSt	TriSt		
SUSPEND	8	12	Driving Low	TriSt	Output	Output
CLKOUT	9	13	Driving Low	Output	Output	Output
INT_n	10	14	Driving High	Output	Output	Output
GL_n	17	21	Driving High	Output	Output	Output
DMREQ	13	17	Driving Low	Output	Output	Output

**Table 16.1 FT120 I/O States**

## 17 FT121 – I/O Pins

FT121						
Pin Name	Pin Number (QFN)	Pin Number (TSSOP)	RESET# Low	SUSPEND	During Enumeration (out of reset)	Active (device enumerated)
MOSI	7	9	TriSt	TriSt	Output	Output
MISO	6	8	TriSt	TriSt	Output	Output

**Table 17.1 FT121 I/O States**

## 18 FT122 – I/O Pins

FT122						
Pin Name	Pin Number (QFN)	Pin Number (TSSOP)	RESET# Low	SUSPEND	During Enumeration (out of reset)	Active (device enumerated)
D0	26	1	TriSt	TriSt	TriSt, driving when RD_N is low and CS_N or DMACK_N is low	TriSt, driving when RD_N is low and CS_N is low or DMACK_N is low
D1	27	2	TriSt	TriSt		
D2	28	3	TriSt	TriSt		
D3	1	4	TriSt	TriSt		
D4	3	6	TriSt	TriSt		
D5	4	7	TriSt	TriSt		
D6	5	8	TriSt	TriSt		
D7	6	9	TriSt	TriSt		
SUSPEND	9	12	Driving Low	TriSt	Output	Output
CLKOUT	10	13	Driving Low	Output	Output	Output
INT_n	11	14	Driving High	Output	Output	Output
GL_n	18	21	Driving High	Output	Output	Output
DMREQ	14	17	Driving Low	Output	Output	Output

**Table 18.1 FT122 I/O States**

## 19 FT313H – I/O Pins

FT313					
Pin Name	Pin Number (QFN)	Pin Number (LQFP)	Pin Number (TQFP)	RESET# Low	Active
AD0	2	2	2	TriSt	Input/Output
AD1	3	3	3	TriSt	Input/Output
AD2	4	4	4	TriSt	Input/Output
AD3	5	5	5	TriSt	Input/Output
AD4	7	7	7	TriSt	Input/Output
AD5	8	8	8	TriSt	Input/Output
AD6	9	9	9	TriSt	Input/Output
AD7	10	10	10	TriSt	Input/Output
AD8	11	11	11	TriSt	Input/Output
AD9	12	12	12	TriSt	Input/Output
AD10	13	13	13	TriSt	Input/Output
AD11	14	14	14	TriSt	Input/Output
AD12	16	16	16	TriSt	Input/Output
AD13	17	17	17	TriSt	Input/Output
AD14	18	18	18	TriSt	Input/Output
AD15	19	19	19	TriSt	Input/Output

**Table 19.1 FT313H I/O States**

## 20 FT4222H Rev A – I/O Pins

### 20.1 Configuration Mode 0

FT4222H CNFMODE0			I/O Status in Revision-A				
Pin Number	Pin Name	Default Function	When Reset	After Reset	During Enumeration	SUSPEND (Default)	Active Function (After Enum.)
8	SCK	SCK (Master)	TriSt	TriSt	Output-Low	(Output-Low)	Function*
9	MISO	MISO (Master)	TriSt	TriSt	TriSt	(Output-Low)	Function*
10	MOSI	MOSI (Master)	Output-High	TriSt	Output-High	(Output-Low)	Function*
11	IO2	IO2 (Master)	TriSt	TriSt	TriSt	(Output-Low)	Function*
12	IO3	IO3 (Master)	TriSt	TriSt	TriSt	(Output-Low)	Function*
13	GPIO0	GPIO0	TriSt	TriSt	Output-Low	(Output-Low)	Function*
14	GPIO1	GPIO1	TriSt	TriSt	Output-Low	(Output-Low)	Function*
15	GPIO2	SUSP_OUT	TriSt	TriSt	Output-Low	(Output-High)	Function**
16	GPIO3	WAKEUP	TriSt	TriSt	TriSt	(TriSt)	Function**
17	SS00	SS00	Output-Low	Output-High	Output-Low	(Output-Low)	Default*
32	SS	SS	TriSt	TriSt	TriSt	TriSt	Default*

**Table 20.1 FT4222H Rev. A I/O States Configuration Mode0**

Default\*: Default means the function is as referred to in the column – “Default Function”

Function\*: Function means that the function for each pin can be selected by the support library(LibFT4222)

Function\*\*: Function means that the function for each pin can be selected by the support library(LibFT4222) or FTDI - FT Prog Setting

(I/O Status): I/O Status with parentheses means the I/O status will be changed by the support library(LibFT4222) or can be set by FTDI - FT Prog Setting



## 20.2 Configuration Mode 1

FT4222H CNFMODE1			I/O Status in Revision-A				
Pin Number	Pin Name	Default Function	When Reset	After Reset	During Enumeration	SUSPEND (Default)	Active Function (After Enum.)
8	SCK	SCK (Master)	TriSt	TriSt	Output-Low	(Output-Low)	Function*
9	MISO	MISO (Master)	TriSt	TriSt	TriSt	(Output-Low)	Function*
10	MOSI	MOSI (Master)	Output-High	TriSt	Output-High	(Output-Low)	Function*
11	IO2	IO2 (Master)	TriSt	TriSt	TriSt	(Output-Low)	Function*
12	IO3	IO3 (Master)	TriSt	TriSt	TriSt	(Output-Low)	Function*
13	GPIO0	SS10 (Master)	TriSt	TriSt	Output-Low	(Output-Low)	Default*
14	GPIO1	SS20 (Master)	TriSt	TriSt	Output-Low	(Output-Low)	Default*
15	GPIO2	SUSP_OUT	TriSt	TriSt	Output-Low	(Output-High)	Function**
16	GPIO3	WAKEUP	TriSt	TriSt	TriSt	(TriSt)	Function**
17	SS00	SS00	Output-Low	Output-High	Output-Low	(Output-Low)	Default*
32	SS	SS	TriSt	TriSt	TriSt	TriSt	Default*

**Table 20.2 FT4222H Rev. A I/O States Configuration Mode1**

Default\*: Default means the function is as referred to in the column – “Default Function”

Function\*: Function means that the function for each pin can be selected by the support library(LibFT4222)

Function\*\*: Function means that the function for each pin can be selected by the support library(LibFT4222) or FTDI - FT Prog Setting

(I/O Status): I/O Status with parentheses means the I/O status will be changed by the support library(LibFT4222) or can be set by FTDI - FT Prog Setting

## 20.3 Configuration Mode 2

FT4222H CNFMODE2			I/O Status in Revision-A				
Pin Number	Pin Name	Default Function	When Reset	After Reset	During Enumeration	SUSPEND (Default)	Active Function (After Enum.)
8	SCK	SCK (Master)	TriSt	TriSt	Output-Low	(Output-Low)	Function*
9	MISO	MISO (Master)	TriSt	TriSt	TriSt	(Output-Low)	Function*
10	MOSI	MOSI (Master)	Output-High	TriSt	Output-High	(Output-Low)	Function*
11	IO2	IO2 (Master)	TriSt	TriSt	TriSt	(Output-Low)	Function*
12	IO3	IO3 (Master)	TriSt	TriSt	TriSt	(Output-Low)	Function*
13	GPIO0	SS10 (Master)	TriSt	TriSt	Output-Low	(Output-Low)	Default*
14	GPIO1	SS20 (Master)	TriSt	TriSt	Output-Low	(Output-Low)	Default*
15	GPIO2	SS30 (Master)	TriSt	TriSt	Output-Low	(Output-Low)	Default*
16	GPIO3	WAKEUP	TriSt	TriSt	TriSt	(TriSt)	Function**
17	SS00	SS00	Output-Low	Output-High	Output-Low	(Output-Low)	Default*
32	SS	SS	TriSt	TriSt	TriSt	TriSt	Default*

**Table 20.3 FT4222H Rev. A I/O States Configuration Mode2**

Default\*: Default means the function is as referred to in the column – “Default Function”

Function\*: Function means that the function for each pin can be selected by the support library(LibFT4222)

Function\*\*: Function means that the function for each pin can be selected by the support library(LibFT4222) or FTDI - FT Prog Setting

(I/O Status): I/O Status with parentheses means the I/O status will be changed by the support library(LibFT4222) or can be set by FTDI - FT Prog Setting

## 20.4 Configuration Mode 3

FT4222H CNFMODE3			I/O Status in Revision-A				
Pin Number	Pin Name	Default Function	When Reset	After Reset	During Enumeration	SUSPEND (Default)	Active Function (After Enum.)
8	SCK	SCK (Master)	TriSt	TriSt	Output-Low	(Output-Low)	Function*
9	MISO	MISO (Master)	TriSt	TriSt	TriSt	(Output-Low)	Function*
10	MOSI	MOSI (Master)	Output-High	TriSt	Output-High	(Output-Low)	Function*
11	IO2	IO2 (Master)	TriSt	TriSt	TriSt	(Output-Low)	Function*
12	IO3	IO3 (Master)	TriSt	TriSt	TriSt	(Output-Low)	Function*
13	GPIO0	GPIO0	TriSt	TriSt	Output-Low	(Output-Low)	Function*
14	GPIO1	GPIO1	TriSt	TriSt	Output-Low	(Output-Low)	Function*
15	GPIO2	SUSP_OUT	TriSt	TriSt	Output-Low	Output-High	Default*
16	GPIO3	WAKEUP	TriSt	TriSt	TriSt	(TriSt)	Default*
17	SS00	SS00	Output-Low	Output-High	Output-Low	(Output-Low)	Default*
32	SS	SS	TriSt	TriSt	TriSt	TriSt	Default*

**Table 20.4 FT4222H Rev. A I/O States Configuration Mode3**

Default\*: Default means the function is as referred to in the column – “Default Function”

Function\*: Function means that the function for each pin can be selected by the support library(LibFT4222)

Function\*\*: Function means that the function for each pin can be selected by the support library(LibFT4222) or FTDI - FT Prog Setting

(I/O Status): I/O Status with parentheses means the I/O status will be changed by the support library(LibFT4222) or can be set by FTDI - FT Prog Setting

## 21 FT4222H Rev B,C,D – I/O Pins

### 21.1 Configuration Mode 0

FT4222H CNFMODE0			I/O Status in Revision-B,C,D				
Pin Number	Pin Name	Default Function	When Reset	After Reset	During Enumeration	SUSPEND (Default)	Active Function (After Enum.)
8	SCK	SCK (Master)	TriSt	TriSt	Output-Low	(TriSt)	Function*
9	MISO	MISO (Master)	TriSt	TriSt	TriSt	(TriSt)	Function*
10	MOSI	MOSI (Master)	Output-High	TriSt	Output-High	(TriSt)	Function*
11	IO2	IO2 (Master)	TriSt	TriSt	TriSt	(TriSt)	Function*
12	IO3	IO3 (Master)	TriSt	TriSt	TriSt	(TriSt)	Function*
13	GPIO0	GPIO0	TriSt	TriSt	TriSt	(TriSt)	Function*
14	GPIO1	GPIO1	TriSt	TriSt	TriSt	(TriSt)	Function*
15	GPIO2	SUSP_OUT	TriSt	TriSt	(Output-Low)	(Output-High)	Function**
16	GPIO3	WAKEUP	TriSt	TriSt	TriSt	(TriSt)	Function**
17	SS00	SS00	Output-Low	Output-High	Output-High	(Output-High)	Default*
32	SS	SS	TriSt	TriSt	TriSt	TriSt	Default*

**Table 21.1 FT4222H Rev. B, C, D I/O States Configuration Mode0**

Default\*: Default means the function is as referred to in the column – “Default Function”

Function\*: Function means that the function for each pin can be selected by the support library(LibFT4222)

Function\*\*: Function means that the function for each pin can be selected by the support library(LibFT4222) or FTDI - FT Prog Setting

(I/O Status): I/O Status with parentheses means the I/O status will be changed by the support library(LibFT4222) or can be set by FTDI - FT Prog Setting

## 21.2 Configuration Mode 1

FT4222H CNFMODE1			I/O Status in Revision-B,C,D				
Pin Number	Pin Name	Default Function	When Reset	After Reset	During Enumeration	SUSPEND (Default)	Active Function (After Enum.)
8	SCK	SCK (Master)	TriSt	TriSt	Output-Low	(TriSt)	Function*
9	MISO	MISO (Master)	TriSt	TriSt	TriSt	(TriSt)	Function*
10	MOSI	MOSI (Master)	Output-High	TriSt	Output-High	(TriSt)	Function*
11	IO2	IO2 (Master)	TriSt	TriSt	TriSt	(TriSt)	Function*
12	IO3	IO3 (Master)	TriSt	TriSt	TriSt	(TriSt)	Function*
13	GPIO0	SS10	TriSt	TriSt	Output-High	(Output-High)	Default*
14	GPIO1	SS20	TriSt	TriSt	Output-High	(Output-High)	Default*
15	GPIO2	SUSP_OUT	TriSt	TriSt	(Output-Low)	(Output-High)	Function**
16	GPIO3	WAKEUP	TriSt	TriSt	TriSt	(TriSt)	Function**
17	SS00	SS00	Output-Low	Output-High	Output-High	(Output-High)	Default*
32	SS	SS	TriSt	TriSt	TriSt	TriSt	Default*

**Table 21.2 FT4222H Rev. B, C, D I/O States Configuration Mode1**

Default\*: Default means the function is as referred to in the column – “Default Function”

Function\*: Function means that the function for each pin can be selected by the support library(LibFT4222)

Function\*\*: Function means that the function for each pin can be selected by the support library(LibFT4222) or FTDI - FT Prog Setting

(I/O Status): I/O Status with parentheses means the I/O status will be changed by the support library(LibFT4222) or can be set by FTDI - FT Prog Setting

## 21.3 Configuration Mode 2

FT4222H CNFMODE2			I/O Status in Revision-B,C,D				
Pin Number	Pin Name	Default Function	When Reset	After Reset	During Enumeration	SUSPEND (Default)	Active Function (After Enum.)
8	SCK	SCK (Master)	TriSt	TriSt	Output-Low	(TriSt)	Function*
9	MISO	MISO (Master)	TriSt	TriSt	TriSt	(TriSt)	Function*
10	MOSI	MOSI (Master)	Output-High	TriSt	Output-High	(TriSt)	Function*
11	IO2	IO2 (Master)	TriSt	TriSt	TriSt	(TriSt)	Function*
12	IO3	IO3 (Master)	TriSt	TriSt	TriSt	(TriSt)	Function*
13	GPIO0	SS10	TriSt	TriSt	Output-High	(Output-High)	Default*
14	GPIO1	SS20	TriSt	TriSt	Output-High	(Output-High)	Default*
15	GPIO2	SS30	TriSt	TriSt	Output-High	(Output-High)	Default*
16	GPIO3	WAKEUP	TriSt	TriSt	TriSt	(TriSt)	Function**
17	SS00	SS00	Output-Low	Output-High	Output-High	(Output-High)	Default*
32	SS	SS	TriSt	TriSt	TriSt	TriSt	Default*

**Table 21.3 FT4222H Rev. B, C, D I/O States Configuration Mode2**

Default\*: Default means the function is as referred to in the column – “Default Function”

Function\*: Function means that the function for each pin can be selected by the support library(LibFT4222)

Function\*\*: Function means that the function for each pin can be selected by the support library(LibFT4222) or FTDI - FT Prog Setting

(I/O Status): I/O Status with parentheses means the I/O status will be changed by the support library(LibFT4222) or can be set by FTDI - FT Prog Setting

## 21.4 Configuration Mode 3

FT4222H CNFMODE3			I/O Status in Revision-B,C,D				
Pin Number	Pin Name	Default Function	When Reset	After Reset	During Enumeration	SUSPEND (Default)	Active Function (After Enum.)
8	SCK	SCK (Master)	TriSt	TriSt	Output-Low	(TriSt)	Function*
9	MISO	MISO (Master)	TriSt	TriSt	TriSt	(TriSt)	Function*
10	MOSI	MOSI (Master)	Output-High	TriSt	Output-High	(TriSt)	Function*
11	IO2	IO2 (Master)	TriSt	TriSt	TriSt	(TriSt)	Function*
12	IO3	IO3 (Master)	TriSt	TriSt	TriSt	(TriSt)	Function*
13	GPIO0	GPIO0	TriSt	TriSt	TriSt	(TriSt)	Function*
14	GPIO1	GPIO1	TriSt	TriSt	TriSt	(TriSt)	Function*
15	GPIO2	SUSP_OUT	TriSt	TriSt	(Output-Low)	(Output-High)	Default*
16	GPIO3	WAKEUP	TriSt	TriSt	TriSt	(TriSt)	Default*
17	SS00	SS00	Output-Low	Output-High	Output-High	(Output-High)	Default*
32	SS	SS	TriSt	TriSt	(TriSt)	TriSt	Default*

**Table 21.4 FT4222H Rev. B, C, D I/O States Configuration Mode3**

Default\*: Default means the function is as referred to in the column – “Default Function”

Function\*: Function means that the function for each pin can be selected by the support library(LibFT4222)

Function\*\*: Function means that the function for each pin can be selected by the support library(LibFT4222) or FTDI - FT Prog Setting

(I/O Status): I/O Status with parentheses means the I/O status will be changed by the support library(LibFT4222) or can be set by FTDI - FT Prog Setting.

## 22 Contact Information

### Head Office – Glasgow, UK

Future Technology Devices International Limited  
Unit 1, 2 Seaward Place, Centurion Business Park  
Glasgow G41 1HH  
United Kingdom  
Tel: +44 (0) 141 429 2777  
Fax: +44 (0) 141 429 2758

E-mail (Sales) [sales1@ftdichip.com](mailto:sales1@ftdichip.com)  
E-mail (Support) [support1@ftdichip.com](mailto:support1@ftdichip.com)  
E-mail (General Enquiries) [admin1@ftdichip.com](mailto:admin1@ftdichip.com)

### Branch Office – Tigard, Oregon, USA

Future Technology Devices International Limited  
(USA)  
7130 SW Fir Loop  
Tigard, OR 97223-8160  
USA  
Tel: +1 (503) 547 0988  
Fax: +1 (503) 547 0987

E-Mail (Sales) [us.sales@ftdichip.com](mailto:us.sales@ftdichip.com)  
E-Mail (Support) [us.support@ftdichip.com](mailto:us.support@ftdichip.com)  
E-Mail (General Enquiries) [us.admin@ftdichip.com](mailto:us.admin@ftdichip.com)

### Branch Office – Taipei, Taiwan

Future Technology Devices International Limited  
(Taiwan)  
2F, No. 516, Sec. 1, NeiHu Road  
Taipei 114  
Taiwan, R.O.C.  
Tel: +886 (0) 2 8797 1330  
Fax: +886 (0) 2 8751 9737

E-mail (Sales) [tw.sales1@ftdichip.com](mailto:tw.sales1@ftdichip.com)  
E-mail (Support) [tw.support1@ftdichip.com](mailto:tw.support1@ftdichip.com)  
E-mail (General Enquiries) [tw.admin1@ftdichip.com](mailto:tw.admin1@ftdichip.com)

### Branch Office – Shanghai, China

Future Technology Devices International Limited  
(China)  
Room 1103, No.666 West Huaihai Road,  
Shanghai, 200052  
China  
Tel: +86 21 62351596  
Fax: +86 21 62351595

E-mail (Sales) [cn.sales@ftdichip.com](mailto:cn.sales@ftdichip.com)  
E-mail (Support) [cn.support@ftdichip.com](mailto:cn.support@ftdichip.com)  
E-mail (General Enquiries) [cn.admin@ftdichip.com](mailto:cn.admin@ftdichip.com)

### Web Site

<http://ftdichip.com>

### Distributor and Sales Representatives

Please visit the Sales Network page of the [FTDI Web site](#) for the contact details of our distributor(s) and sales representative(s) in your country.

System and equipment manufacturers and designers are responsible to ensure that their systems, and any Future Technology Devices International Ltd (FTDI) devices incorporated in their systems, meet all applicable safety, regulatory and system-level performance requirements. All application-related information in this document (including application descriptions, suggested FTDI devices and other materials) is provided for reference only. While FTDI has taken care to assure it is accurate, this information is subject to customer confirmation, and FTDI disclaims all liability for system designs and for any applications assistance provided by FTDI. Use of FTDI devices in life support and/or safety applications is entirely at the user's risk, and the user agrees to defend, indemnify and hold harmless FTDI from any and all damages, claims, suits or expense resulting from such use. This document is subject to change without notice. No freedom to use patents or other intellectual property rights is implied by the publication of this document. Neither the whole nor any part of the information contained in, or the product described in this document, may be adapted or reproduced in any material or electronic form without the prior written consent of the copyright holder. Future Technology Devices International Ltd, Unit 1, 2 Seaward Place, Centurion Business Park, Glasgow G41 1HH, United Kingdom. Scotland Registered Company Number: SC136640



## Appendix A – References

### Document References

- [FT232R USB UART IC Data Sheet](#)
- [FT245R USB FIFO Data Sheet](#)
- [FT232H Single Channel Hi-Speed USB to Multipurpose UART/FIFO IC Data Sheet](#)
- [FT2232H Hi-Speed Dual USB UART/FIFO IC Data Sheet](#)
- [FT4232H Hi-Speed Quad USB UART IC Data Sheet](#)
- [FT2232D Dual USB UART/FIFO IC Data Sheet](#)
- [FT200XD Full-Speed USB to I2C bridge in 10 pin DFN package Data Sheet](#)
- [FT201X Full-Speed USB to I2C bridge Data Sheet](#)
- [FT220X Full-Speed USB to 4-bit SPI/FT1248 bridge Data Sheet](#)
- [FT221X Full-Speed USB to 8-bit SPI/FT1248 bridge Data Sheet](#)
- [FT230X Full-Speed USB to basic UART Data Sheet](#)
- [FT231X Full-Speed USB to full handshake UART Data Sheet](#)
- [FT234XD Full-Speed USB to basic UART Data Sheet](#)
- [FT240X Full-Speed USB to 8-bit FIFO Data Sheet](#)
- [FT120 USB Full-Speed Device Controller Data Sheet](#)
- [FT121 USB Full-Speed Device Controller Data Sheet](#)
- [FT122 USB Full-Speed Device Controller Data Sheet](#)
- [FT313H Hi-Speed Host Controller](#)
- [FT4222H Hi-Speed Quad SPI/I2C IC Data Sheet](#)

### Acronyms and Abbreviations

Terms	Description
PD	Internal pull-down resistor to GND
PU	Internal pull-up resistor to VCCIO
TriSt	High-impedance off-state ('tristate')
USB	Universal Serial Bus
USB-IF	USB Implementers Forum

## Appendix B – List of Tables & Figures

### List of Tables

Table 2.1	FT232R I/O States .....	4
Table 2.2	FT232R CBUS Selected Functions .....	5
Table 3.1	FT245R I/O States .....	6
Table 4.1	FT232H I/O States .....	7
Table 4.2	FT232H Selected Functions .....	8
Table 5.1	FT2232H I/O States Channel A .....	9
Table 5.2	FT2232H I/O States Channel B .....	10
Table 5.3	FT2232H Selected Functions.....	11
Table 6.1	FT4232H I/O States Channel A .....	12
Table 6.2	FT4232H I/O States Channel B .....	12
Table 6.3	FT4232H I/O States Channel C .....	13
Table 6.4	FT4232H I/O States Channel D .....	13
Table 6.5	Selected Functions .....	14
Table 7.1	FT2232D I/O States Channel A .....	15
Table 7.2	FT2232D I/O States Channel B .....	16
Table 7.3	Pin Definition by Chip Mode - Channel A .....	17
Table 7.4	Pin Definition by Chip Mode - Channel B .....	18
Table 8.1	FT200XD I/O States .....	19
Table 9.1	FT201X I/O States .....	20
Table 10.1	FT220X I/O States.....	21
Table 11.1	FT221X I/O States.....	22
Table 12.1	FT230X I/O States.....	23
Table 13.1	FT231X I/O States.....	24
Table 14.1	FT234XD I/O States .....	25
Table 15.1	FT240X I/O States.....	26
Table 16.1	FT120 I/O States .....	27
Table 17.1	FT121 I/O States .....	28
Table 18.1	FT122 I/O States .....	29
Table 19.1	FT313H I/O States .....	30
Table 20.1	FT4222H Rev. A I/O States Configuration Mode0.....	31
Table 20.2	FT4222H Rev. A I/O States Configuration Mode1.....	32
Table 20.3	FT4222H Rev. A I/O States Configuration Mode2.....	33
Table 20.4	FT4222H Rev. A I/O States Configuration Mode3.....	34
Table 21.1	FT4222H Rev. B, C, D I/O States Configuration Mode0.....	35
Table 21.2	FT4222H Rev. B, C, D I/O States Configuration Mode1.....	36



Table 21.3 FT4222H Rev. B, C, D I/O States Configuration Mode2.....	37
Table 21.4 FT4222H Rev. B, C, D I/O States Configuration Mode3.....	38

## List of Figures

NA

## Appendix C – Revision History

Document Title: AN\_184 FTDI Device Input Output Pin States  
Document Reference No.: FT\_000507  
Clearance No.: FTDI#237  
Product Page: <http://www.ftdichip.com/FTProducts.htm>  
Document Feedback: [Send Feedback](#)

Revision	Changes	Date
1.0	Initial Release	2011-11-24
2.0	Updated to include FT-X series, FT12 series & FT313H	2012-03-13
3.0	Updated to include FT4222H	2015-09-10
3.1	Updated FT4222H rev. D I/O Pins in section 21. Updated Table 2.2 Bit bang WR# strobe CBUS availability.	2018-04-19